



DIMENSIONS IN MM										
VA RATING	A	B	C	D	E	F	G	H	I	J
50VA	75	88	68	58	72	1.5	56	4.5	42	48
100VA	85	94	74	60	74	1.5	64	4.5	42	48
150VA	96	103	86	78	84	2	84	5.5	58	68
200VA	96	103	86	88	93	2	84	5.5	66	76
250VA	120	120	104	89	90	2	90	5.5	68	78
300VA	120	120	104	102	102	2	90	5.5	80	90
400VA	120	120	104	108	110	2	90	5.5	87	97
500VA	120	120	104	120	120	2	90	5.5	109	119
750VA	150	144	130	105	98	3	122	6.5	78	90
1KVA	150	144	130	122	116	3	122	6.5	96	108
1.5KVA	150	144	130	148	141	3	122	6.5	122	134

MV TRANSFORMER VA AND VOLTAGE TYPES

VOLTAGE TYPES:

INPUT P1-10/0/220/240V OUTPUT S1 0/55/110V
 INPUT P2-20/0/380/420V OUTPUT S1-0/55/110VV

VA RATINGS:

50VA all voltage types above
 100VA all voltage types above
 150VA all voltage types above
 200VA all voltage types above
 250VA all voltage types above
 300VA all voltage types above
 400VA all voltage types above
 500VA all voltage types above
 750VA all voltage types above
 1kVA all voltage types above
 1.5kVA all voltage types above

Input terminals 4mm sq

Output terminals 4mm sq

Drawing Number TX 41029001	
Title	MV TRANSFORMERS 4 SM & 3 SM TERMINALS
Project	STOCK TRANSFORMERS
Drawn Date	01/09/2014
Sheet Number	1 Of 1
Drawn By	RDT
Scale	NTS Revision 1
Company Name	Eastern Transformers & Equipment Ltd
	Units H1 & H2 Overland Business Park Great Whelnetham Bury St Edmunds, Suffolk, ENGLAND, IP30 0UL
Telephone No	0044 (0) 1284 388033
Email Address	info@ete.co.uk
Web Address	www.ete.co.uk