



WV TRANSFORMER VA AND VOLTAGE TYPES

VOLTAGE TYPES:

INPUT

P7- 0/380/400/420/440/460/480V

OUTPUTS

S7- 0/24V 0/24V for series or parallel connection
or
S8- 0/110V 0/110V for series or parallel connection

VA RATINGS:

50VA all voltage types above
100VA all voltage types above
150VA all voltage types above
200VA all voltage types above
250VA all voltage types above
300VA all voltage types above
400VA all voltage types above
500VA all voltage types above
750VA all voltage types above
1kVA all voltage types above
1.5kVA all voltage types above

Input terminals 4mm sq

Output terminals 4mm sq

DIMENSIONS IN MM										
VA RATING	A	B	C	D	E	F	G	H	I	J
50VA	75	88	68	58	72	1.5	56	4.5	42	48
100VA	85	94	74	60	74	1.5	64	4.5	42	48
150VA	96	103	86	78	84	2	84	5.5	58	68
200VA	96	103	86	88	93	2	84	5.5	66	76
250VA	120	120	104	89	90	2	90	5.5	68	78
300VA	120	120	104	102	102	2	90	5.5	80	90
400VA	120	120	104	108	110	2	90	5.5	87	97
500VA	120	120	104	120	120	2	90	5.5	109	119
750VA	150	144	130	105	98	3	122	6.5	78	90
1KVA	150	144	130	122	116	3	122	6.5	96	108
1.5KVA	150	144	130	148	141	3	122	6.5	122	134

Drawing Number TX 41029003	
Title	WV TRANSFORMERS 7 SM & 4 SM TERMINALS
Project	STOCK TRANSFORMERS
Drawn Date	01/09/2014
Sheet Number	1 Of 1
Drawn By	RDT
Scale	NTS Revision 1
Company Name	Eastern Transformers & Equipment Ltd
Units H1 & H2 Overland Business Park Great Whelnetham Bury St Edmunds, Suffolk, ENGLAND, IP30 0UL	
Telephone No	0044 (0) 1284 388033
Email Address	info@ete.co.uk
Web Address	www.ete.co.uk