



DV TRANSFORMER VA AND VOLTAGE TYPES

VOLTAGE TYPES:

INPUT
P6 0/240/415V

Outputs
S4 0/110v
or
S5 0/240v
or
S6 0/24v

VA RATINGS:

50VA all voltage types above
100VA all voltage types above
150VA all voltage types above
200VA all voltage types above
250VA all voltage types above
300VA all voltage types above
400VA all voltage types above
500VA all voltage types above
750VA
P6-0/240/415V OUTPUT S4-0/110V
P6-0/240/415V OUTPUT S5-0/240V
1kVA all voltage types above
P6-0/240/415V OUTPUT S4-0/110V
P6-0/240/415V OUTPUT S5-0/240V

Input terminals 4mm sq

Output terminals 4mm sq

DIMENSIONS IN MM										
VA RATING	A	B	C	D	E	F	G	H	I	J
50VA	75	88	68	65	80	1.5	56	4.5	49	55
100VA	85	94	74	72	84	1.5	64	4.5	56	62
150VA	96	103	86	88	90	2	84	5.5	67	77
200VA	96	103	86	100	106	2	84	5.5	79	89
250VA	120	120	104	89	90	2	90	5.5	68	78
300VA	120	120	104	102	102	2	90	5.5	80	90
400VA	120	120	104	108	110	2	90	5.5	87	97
500VA	135	128	114	104	105	2	105	5.0	84	94
750VA	150	144	130	105	98	3	122	6.5	78	90
1KVA	150	144	130	122	116	3	122	6.5	96	108

Drawing Number TX 41029004	
Title	DV TRANSFORMERS 3 SM & 2 SM TERMINALS
Project	STOCK TRANSFORMERS
Drawn Date	01/09/2014
Sheet Number	1 Of 1
Drawn By	RDT
Scale	NTS Revision 1
Company Name	Eastern Transformers & Equipment Ltd
	Units H1 & H2 Overland Business Park Great Whelnetham Bury St Edmunds, Suffolk, ENGLAND, IP30 0UL
Telephone No	0044 (0) 1284 388033
Email Address	info@ete.co.uk
Web Address	www.ete.co.uk